

## 2600W Petrol Powerlite Generator Model PH033 Powered by Honda

Made in  
Australia

2600W

Honda  
Engine

2  
Outlets



**Safety Yellow Frame**



### Specifications

Industry rating	3.3
Real Power	2600 watts
Engine	GX200 Honda
Starting	Recoil
Phase	Single
Fuel	Petrol
Frame	Roll
Tank Litres	3.6
Fuel litres per hour	1.3
Weight	40 kg
Outlets	2 x 10A
Dimensions (LxWxH mm)	630x420x450

**Phone:** 1300 436 738 **Email:** [sales@powerlite.com.au](mailto:sales@powerlite.com.au) **Website:** [powerlite.com.au](http://powerlite.com.au)  
**Address:** 2 Binney Road, Kings Park NSW 2148

Powerlite Australia reserves the right to make changes in mode, technical specifications, colour configuration and accessories.  
Powerlite Australia Pty Limited ABN: 34 083 604 004



Powerlite Australia is an ISO9001  
quality certified company

